

4 1/2 & 3 1/2 DIGITAL MULTIMETER



GDM-8145 (4 1/2 Digits)



GDM-8135 (3 1/2 Digits)



FEATURES

- * Vast Measuring Functions : AC/DC Voltage, AC/DC Current, Resistance and Diode Test
- * Continuity Beeper (GDM-8135)
- * Large 0.5" Red LED Display
- * High Resolution 10 μ V, 10nA and 10m Ω
- * All Range with Protection Circuit
- * 0.03% DCV Accuracy (GDM-8145), 0.1% DCV Accuracy (GDM-8135)
- * Auto Zero Circuit
- * 20A High Current Range
- * 1000V High Voltage Range
- * AC or AC + DC True RMS (GDM-8145)

GTL-107A Test Lead

For: GDM-8034, GDM-8135, GDM-8145



In terms of cost/performance ratio, the GDM-8145/8135 Series yield one of the best choices among the DMMs in today's market. The series are equipped with 4 1/2 (GDM-8145) or 3 1/2 (GDM-8135) digits, 0.5" LED display in a distinctive red color. Measurement items include DC Voltage/Current, AC Voltage/Current with true RMS (GDM-8145), Resistance, Diode Test, and Continuity with Beeper (GDM-8135). The true RMS AC and AC+DC response give accurate measurements for equivalent DC energy regardless of the waveform shape. Small voltage offsets are canceled by the auto-zero circuit, and protection mechanism is available for the entire measurement range. All these features provide users with robust measurement experience.

SPECIFICATIONS		
	GDM-8145	GDM-8135
DC VOLTAGE		
Range	200mV, 2V, 20V, 200V, 1000V 5 ranges.	200mV, 2V, 20V, 200V, 1000V 5 ranges
Accuracy	$\pm(0.03\% \text{ rdg} + 4 \text{ digits})$	$\pm(0.1\% \text{ rdg} + 1 \text{ digit})$
Input Impedance	10M	10M
AC VOLTAGE		
Range	200mV, 2V, 20V, 200V, 1000V 5 ranges	200mV, 2V, 20V, 200V, 1000V 5 ranges
Accuracy	200mV ~ 20V 4 ranges 20Hz ~ 45Hz $\pm(1\% \text{ rdg} + 15 \text{ digits})$ 45Hz ~ 2kHz $\pm(0.5\% \text{ rdg} + 15 \text{ digits})$ 2kHz ~ 10kHz $\pm(1\% \text{ rdg} + 15 \text{ digits})$ 10kHz ~ 20kHz $\pm(2\% \text{ rdg} + 30 \text{ digits})$ 20kHz ~ 50kHz $\pm(5\% \text{ rdg} + 30 \text{ digits})$ 200V~1000V range : 45Hz ~ 1kHz $\pm(0.5\% \text{ rdg} + 15 \text{ digits})$	200mV ~ 20V 3 ranges : 40Hz ~ 1kHz $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$ 1kHz ~ 10kHz $\pm(1\% \text{ rdg} + 1 \text{ digit})$ 10kHz ~ 20kHz $\pm(2\% \text{ rdg} + 1 \text{ digit})$ 20kHz ~ 40kHz $\pm(5\% \text{ rdg} + 1 \text{ digit})$ 200V range : 40Hz ~ 1kHz $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$; 1kHz ~ 10kHz $\pm(1\% \text{ rdg} + 1 \text{ digit})$ 1000V range : 40Hz ~ 1kHz $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$
Input Impedance	10M	10M
DC CURRENT		
Range	200 μ A, 2mA, 20mA, 200mA, 2000mA, 20A 6 ranges	200 μ A, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	200 μ A ~ 200mA 4 ranges $\pm(0.2\% \text{ rdg} + 2 \text{ digits})$ 2000mA ~ 20A 2 ranges $\pm(0.3\% \text{ rdg} + 2 \text{ digits})$	200 μ A ~ 200mA 4 ranges : $\pm(0.2\% \text{ rdg} + 1 \text{ digit})$ 2A ~ 20A 2 ranges : $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$
AC CURRENT		
Range	200 μ A, 2mA, 20mA, 200mA, 2000mA, 20A 6 ranges	200 μ A, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	200 μ A ~ 200mA 4 ranges 45Hz ~ 2kHz $\pm(0.5\% \text{ rdg} + 15 \text{ digits})$ 2kHz ~ 10kHz $\pm(1\% \text{ rdg} + 15 \text{ digits})$ 10kHz ~ 20kHz $\pm(2\% \text{ rdg} + 15 \text{ digits})$ 2000mA ~ 20A 2 ranges 45Hz ~ 2kHz $\pm(0.5\% \text{ rdg} + 15 \text{ digits})$	200 μ A ~ 200mA 4 ranges 40Hz ~ 1kHz $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$ 1kHz ~ 10kHz $\pm(1\% \text{ rdg} + 1 \text{ digit})$ 10kHz ~ 20kHz $\pm(2\% \text{ rdg} + 1 \text{ digit})$ 2A ~ 20A 2 ranges, 40Hz ~ 2kHz $\pm(1\% \text{ rdg} + 2 \text{ digits})$
RESISTANCE		
Range	200 , 2k , 20k , 200k , 2000k , 20M 6 ranges	200 , 2k, 20k, 200k , 2M , 20M 6 ranges.
Accuracy	200 : $\pm(0.1\% \text{ rdg} + 4 \text{ digits})$ 2k ~ 200k : $\pm(0.1\% \text{ rdg} + 2 \text{ digits})$ 2000k ~ 20M : $\pm(0.25\% \text{ rdg} + 2 \text{ digits})$	200 ~ 2M 5 ranges : $\pm(0.2\% \text{ rdg} + 1 \text{ digit})$ 20M range : $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$
DIODE TEST		
Test Current	Max. 1 mA	Max. 1 mA
Open Voltage	Max. 13V	Max. 13V
CONTINUITY BEEPER		
Description	—	Buzzer sounds if conductance < 10 Ω
Test Current	—	Max. 1 mA
Open Voltage	—	Max. 13V
DISPLAY		
0.5" LED display		
POWER SOURCE		
AC 100V/120V/220V/230V $\pm 10\%$, 50/60Hz		
DIMENSIONS & WEIGHT		
245(W) x 95(H) x 280(D) mm, Approx. 2kg		

ORDERING INFORMATION

GDM-8145 4 1/2 Digits True RMS Digital Multimeter
GDM-8135 3 1/2 Digits Digital Multimeter

ACCESSORIES :
 User manual x 1, Power cord x 1, Test lead GTL-107A x 1

Available from



CALTEST
Instruments Ltd
Specialists in power
and instrumentation

Power sources and test instrumentation solutions

Caltest have been providing power sources and test instrumentation solutions for over 20 years and are proud to represent a number of industry leading manufacturers.

As well as supplying world class power sources and test instrumentation Caltest also has a service centre and UKAS calibration laboratory.

NEED HELP?

CALL US:

01483 302 700

or visit our website for more details

Caltest Instruments Ltd
4 Riverside Business Centre
Walnut Tree Close
Guildford
Surrey GU1 4UG
United Kingdom

Tel: +44 (0) 1483 302 700

Fax: +44 (0) 1483 300 562

sales@caltest.co.uk

www.caltest.co.uk

Sales • Rentals • Service • UKAS Calibration

